

Fujikura 38S

NEW

Features

- Core loss estimation function
- Touch panel with easy operation
- Bluetooth capability connection
- Multi-functional carrying case with integrated work station



Single Fiber Fusion Splicer

Fujikura 38S

Active V-groove Alignment

SPECIFICATIONS

Applicable fiber	Single / SMF(G.652/657), MMF(G.651), DSF(G.653), NZDSF(G.655)
Cladding dia. / Sheath dia.	125 μ m / Up to 3mm with sheath clamp
Cleave length	5mm to 16mm
Splice mode / heating mode	Total 100 splice modes / 30 heating modes
Typical splice loss*1	0.03dB (SM), 0.01dB(MM), 0.05dB(DS) and 0.05dB(NZDS)
Return loss	>>60dB
Typical Splice time	6sec SM FAST, 9sec SM AUTO
Typical Tube heating time	25sec FP-03, coating dia.250 μ m
Splice result storage	Last 10,000 splices
Viewing methods / magnification	2 axis 2CMOS camera with 5.0" color LCD. 132X magnification.200X magnification after splicing
Tension test	1.96 to 2.25N
Applicable protection sleeve	60mm, 40mm and Fujikura micro sleeves
No. of splice / heating per battery full charge*2	Typical 200 cycles with BTR-11
Electrode life	Typical 5000 splices
Wireless connectivity	Wireless technical standard : Bluetooth®4.1LE*3 OS : Andoroid 5.0 or above, ios 8.0 or above (iphone6 above)
Size / weight	131W x 201D x 79H mm / 1300g (including battery)
Operating condition	Altitude : 0 to 5,000m above sea level, Wind : 15m/sec*4 Temperature : -10 to 50deg C, Humidity : 0 to 95%RH, non-dew
Resistance feature*5	Shock resistance : 76cm (30inch) bottom surface drop Dust resistance : Exposure to dust (0.1 to 500 μ m dia. Alumina Silicate) ,IP5X Rain resistance : H=10mm/hr for 10min ,IPX2
Other features	PC software upgrade / data management
Terminals	USB 2.0 (Mini-B type) connector for PC communication.

*1:Typical value of the inspection with Fujikura identical fiber. Measured by cut-back method relevant to ITU-T and IEC standards.

*2:one(1) splicing and heating cycle per two(2) min. under room temperature condition.

*3:The Bluetooth wireless connection of this product is not guaranteed to work with all smartphones or other devices.

*4:Under strong wind, it is necessary to lengthen the heating time setting.

*5:The shock, dust and rain resistance test do not guarantee the product will not be damaged under these conditions.

Single Fiber Fusion Splicer
Fujikura 38S
Active V-groove Alignment

STANDARD PACKAGE

Description	Model No.	Q'ty
Fusion splicer	38S	1pc
Built in battery pack*5	BTR-11(Li-ion)*6	1pc
Fiber Cleaver	CT-50(for single to 12 ribbon fibers)	1pc
Set plate	SP-31	1pc
AC adapter	ADC-19A	1pc
AC power cord	ACC-11	1pc
Carrying case	CC-36	1pc
Single Fiber Stripper	3 in one stripper	1pc
Spare electrodes	ELCT2-16B	1pair
Instruction manual CD	M-41	1pc
Quick reference guide	Q-41S-E	1pc

OPTIONAL ITEMS

Description	Model No.
Fiber holder	FH-60-250 (coating dia. of 250µm)
	FH-60-900 (coating dia. of 900µm)
	FH-60-DC250 (coating dia. of 250µm in drop cable)
	FH-FC-20 (coating dia. of 900µm in 2.0mm Sheath dia.)
	FH-FC-30 (coating dia. of 900µm in 3.0mm Sheath dia.)
	FH-60-LT900 (900µm dia. loose buffer fiber)
Sheath clamp	CLAMP-S31A (included in standard package)
	CLAMP-S31B (900µm dia. loose buffer fiber)
Fiber Cleaver	CT-08 (For Single Fiber)

*6:all senders have to ovey the IATA regulation in case of Li-ion battery transportation by air.

Please visit **NEW** web site!

<http://www.keithelectronics.in>

Fujikura 38S



TOLL FREE NO : 1800-1020-429

 **Facebook**
<https://www.facebook.com/KeithElectronics01>

 **twitter**
<https://twitter.com/fujikurasplicer>

NEW

Specifications and descriptions are subject to change without prior notice. © 2018 Fujikura Ltd.

Keith Electronics Pvt. Ltd.

429, Ansal Chambers-II, 6, Bhikaji Cama Place, New Delhi-110 066 INDIA
 Phone: 9312266960, 8527998815, 011-26169380-81, Fax: 011-41658648
 E-mail : keithelectronics@airtelmail.in, infofuji@kepl.co.in
 Website: www.keithelectronics.com



-: **Branches** :-

Ahmedabad, Bangalore, Bhopal, Chennai, Cochin, Guwahati, Hyderabad, Jaipur, Jammu, Kolkata, Lucknow, Mumbai, Nagpur, Patna, Raipur, Trichy & Vijyawada